Keyboard shortcuts

XL Term

BBS terminal for Atari XL and XE computers

^ means CONTROL: ^S is CONTROL and S.

Terminal

Everything you type goes to the BBS

ESC	Menu (no Ctrl shortcuts)
RETURN	Carriage return (EOL in ATASCII)
Arrows	VT100 cursor keys
Ctrl+letter	Sent to the BBS

Phone book

Connection > Phone book and dial

1–8	Connect
E	Edit an entry
N:...	FujiNet: N:TELNET://host:23/
ATDT...	Modem on R1:

Connection menu

Capture up to 8 KB

Hang up	+++, ATH and DTR off on R:
Capture	On / off
Save capture	A .TXT file
Clear screen	Empty terminal
Quit	Back to DOS

Settings

Mode	ASCII (VT100) / ATASCII
Baud rate	300-9600 (R:)
Local echo	On / off
Save	PHONES.XLK

You need

FujiNet	N: or R: handler
850 + modem	R: handler

Load the R: or N: handler before XL Term. 2400 baud recommended on R:.